

# 365 True-rms AC/DC Clamp Meter

Rugged meters where access is difficult

## Technical Data

### Measurement capability

- 200 A ac and dc current measurement with detachable jaw
- 600 V ac and dc voltage measurement
- True-rms ac voltage and current for accurate measurements on non-linear signals
- 6000  $\Omega$  resistance measurement with continuity detection

### Features

- Detachable jaw makes accessing wires and viewing the display easier
- Built in flashlight/torch allows for easy illumination and identification of wires
- CAT III 600 V safety rating
- Compact design fits in your hand and can be used while wearing personal protective equipment
- State of the art signal processing allows for use in noisy electrical environments while providing stable readings
- Large, easy to read backlight display automatically sets the correct measurement range so you do not need to change switch positions while taking a measurement
- Three-year warranty
- Soft case

The Fluke 365 is a new, innovative Fluke clamp meter, offering a thin, small jaw design that makes it easy to get around tightly packed wires. The detachable jaw on a flexible lead makes access to wires and viewing the display easier than ever. The Fluke 365 measures current up to 200 A ac and dc with true-rms measurement.



**Specifications**

Fluke 365	Range	Resolution	Accuracy
AC current	200 A	0.1 A	2 % ± 5 digits
DC current	200 A	0.1 A	2 % ± 5 digits
AC voltage	600 V	0.1 V	2 % ± 5 digits
DC voltage	600 V	0.1 V	2 % ± 5 digits
Resistance	6000 Ω	0.1 Ω	1 % ± 5 digits
True-rms	•		
Continuity	•		
Hold	•		
Backlight	•		
Flashlight/torch	•		
Wire capacity	17 mm		
Safety rating	CAT III 600 V		

**Ordering information**

365 True-rms AC/DC  
Clamp Meter

**Included**

Clamp meter, test leads, soft case, users manual.

**Fluke.** *Keeping your world up and running.®*

Modification of this document is not permitted without written permission from Fluke Corporation.